



Organisme belge d'Accréditation  
Belgische Accreditatieinstelling  
Belgische Akkreditierungsstelle  
Belgian Accreditation Body

EA MLA Signatory

Bijlage bij accreditatie-certificaat  
Annexe au certificat d'accréditation  
Annex to the accreditation certificate  
Beilage zur Akkreditierungszertifikat

# 001-CAL

EN ISO/IEC 17025:2017

Versie / Version / Version / Fassung	22
Geldigheidsperiode / Validité / Validity / Gültigkeitsdauer	2023-12-08 - 2026-06-01

**Maureen Logghe**

Voorzitster van het Accreditatiebureau  
La Présidente du Bureau d'Accréditation  
Chair of the Accreditation Board  
Vorsitzende des Akkreditierungsbüro

De accreditatie werd uitgereikt aan / L'accréditation est délivrée à /  
The accreditation is granted to / Die akkreditierung wurde erteilt für:

**TRESCAL nv**  
**Vosstraat, 200**  
**2600 Antwerpen**

Activiteitencentra / Sites d'activités / Sites of activities / Standorte mit aktivitäten:

Locatie 1 - WOMMELGEM	Nijverheidsstraat, 70 2160 Wommelgem
Locatie 2 - WELLIN	Rue Jean Meunier, 2 6922 Wellin
Locatie 3 - LOUVAIN-LA-NEUVE	Rue du Bosquet, 7 1348 Ottignies-Louvain-la-Neuve

**DCLF Electricity Wommelgem (In House or Onsite)**

**Calibration and Measurement Capabilities**

Direct voltage  
Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	Location
± 100 mV	DC	$5,0 \times 10^{-6} \times U$	• Transfer standard in "30 day" loop • Fixed points • positive /negative • measuring	P2-02-E.006	AN, OS
± 1 V	DC	$2,7 \times 10^{-6} \times U$			
± 10 V	DC	$2,1 \times 10^{-6} \times U$			
± 19 V	DC	$2,3 \times 10^{-6} \times U$			
± 100 V	DC	$3,0 \times 10^{-6} \times U$			
± 1000 V	DC	$3,0 \times 10^{-6} \times U$			

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 mV to 200 mV	DC	$7,0 \times 10^{-6} \times U$ or $0,1 \mu\text{V}^1$	• measure • positive / negative	P2-02-E.019	AN , OS
0,2 V to 2 V	DC	$5,0 \times 10^{-6} \times U$			
2 V to 20 V	DC	$4,5 \times 10^{-6} \times U$			
20 V to 200 V	DC	$5,5 \times 10^{-6} \times U$			
200 V to 1000 V	DC	$5,5 \times 10^{-6} \times U$			
1 kV to 75 kV	DC	$3,0 \times 10^{-4} \times U$	Measure	P2-02-E.016	
0,2 V to 11 V	DC	$1,0 \times 10^{-4} \times U$	Loop calibration	P2-02-E.019	OS

<sup>1</sup> Whichever is greater

Direct voltage Generate					
Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
100 mV	DC	$1,5 \times 10^{-6} \times U$	• generate / measure • Fixed points with Zener	PZ2-02-E.001	AN
1 V, 10 V, 100 V	DC	$1 \times 10^{-6} \times U$			
1000 V	DC	$1,2 \times 10^{-6} \times U$			
Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 mV to 200 mV	DC	$18 \times 10^{-6} \times U$ or $0,5 \mu\text{V}^1$	• generate • positive / negative	P2-02-E.005	AN, OS
0,2 V to 2 V	DC	$8,0 \times 10^{-6} \times U$			
2 V to 20 V	DC	$4,5 \times 10^{-6} \times U$			
20 V to 200 V	DC	$7,0 \times 10^{-6} \times U$			
200 V to 1100 V	DC	$10 \times 10^{-6} \times U$			
1,1 kV to 40 kV	DC	$3,0 \times 10^{-4} \times U$	Generate	P2-02-E.016	
0,2 V to 11 V	DC	$1,0 \times 10^{-4} \times U$	Loop calibration	P2-02-E.005	OS

<sup>1</sup> Whichever is greater

Direct current

Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
$\pm 100 \mu\text{A}$	DC	$24 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>positive / negative</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
$\pm 1 \text{ mA}$	DC	$16 \times 10^{-6} \times I$			
$\pm 10 \text{ mA}$	DC	$16 \times 10^{-6} \times I$			
$\pm 100 \text{ mA}$	DC	$19 \times 10^{-6} \times I$			
$\pm 1 \text{ A}$	DC	$31 \times 10^{-6} \times I$			
$\pm 10 \text{ A}$	DC	$60 \times 10^{-6} \times I$			
Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
1 A to 10 A	DC	$2 \times 10^{-5} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>positive / negative</li> <li>with standard resistances</li> </ul>	P2-02-E.022	AN
100 mA to 1 A	DC	$1 \times 10^{-5} \times I$			
100 nA to 100 mA	DC	$5 \times 10^{-6} \times I$			
100 nA to 10 nA	DC	$6 \times 10^{-5} \times I$			
10 nA to 1 nA	DC	$1 \times 10^{-4} \times I$			
1 nA to 100 pA	DC	$3 \times 10^{-4} \times I$			
100 pA to 10 pA	DC	$1 \times 10^{-3} \times I$			
10 pA to 1 pA	DC	$2 \times 10^{-3} \times I$			
Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 $\mu\text{A}$ to 200 $\mu\text{A}$	DC	$12 \times 10^{-6} \times I$ or $0,5 \text{ nA}^1$	<ul style="list-style-type: none"> <li>measure</li> <li>in the lowest possible range</li> <li>positive / negative</li> </ul>	P2-02-E.019	AN, OS
0,2 mA to 2 mA	DC	$11 \times 10^{-6} \times I$			
2 mA to 20 mA	DC	$9,0 \times 10^{-6} \times I$			
20 mA to 200 mA	DC	$16 \times 10^{-6} \times I$			
0,2 A to 2 A	DC	$90 \times 10^{-6} \times I$			
2 A to 20 A	DC	$90 \times 10^{-6} \times I$			
0,2 mA to 24 mA	DC	$1,0 \times 10^{-4} \times I$	Loop calibration	P2-02-E.019	OS

<sup>1</sup> Whichever is greater

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
20 A to 3000 A	DC	$2,0 \times 10^{-4} \times I$	measure/generate	P2-02-E.030	AN, OS

Calibration of current clamps

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
20 A to 1000 A	DC	$5,0 \times 10^{-3} \times I$	• with current coils	P2-02-E.021	AN, OS

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 $\mu\text{A}$ to 20 $\mu\text{A}$	DC	$1,5 \text{ nA}$	<ul style="list-style-type: none"> <li>generate</li> <li>positive / negative</li> </ul>	P2-02-E.005	AN, OS
20 $\mu\text{A}$ to 200 $\mu\text{A}$	DC	$1,7 \times 10^{-4} \times I$			
0,2 mA to 200 mA	DC	$0,70 \times 10^{-4} \times I$			
0,2 A to 2 A	DC	$1,9 \times 10^{-4} \times I$			
2 A to 11 A	DC	$2,7 \times 10^{-4} \times I$			
11 A to 20 A	DC	$6,0 \times 10^{-4} \times I$			
0,2 mA to 24 mA	DC	$1,0 \times 10^{-4} \times I$	Loop calibration	P2-02-E.005	OS

## Alternating voltage

## Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
1 mV	20 Hz to 20 kHz	$3,0 \times 10^{-4} \times U + 2 \mu\text{V}$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	30 kHz & 50 kHz	$4,0 \times 10^{-4} \times U + 2 \mu\text{V}$			
	100 kHz	$6,5 \times 10^{-4} \times U + 2 \mu\text{V}$			
10 mV	20 Hz to 20 kHz	$1,7 \times 10^{-4} \times U + 2 \mu\text{V}$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	30 kHz & 50 kHz	$2,5 \times 10^{-4} \times U + 2 \mu\text{V}$			
	100 kHz	$4,5 \times 10^{-4} \times U + 2 \mu\text{V}$			
100 mV	20 Hz to 20 kHz	$1,2 \times 10^{-4} \times U + 2 \mu\text{V}$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	30 kHz & 50 kHz	$2,0 \times 10^{-4} \times U + 2 \mu\text{V}$			
	100 kHz	$4,0 \times 10^{-4} \times U + 2 \mu\text{V}$			
1 V	10 Hz to 30 Hz	$4,0 \times 10^{-5} \times U$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 30 kHz	$3,0 \times 10^{-5} \times U$			
	50 kHz	$4,0 \times 10^{-5} \times U$			
	100 kHz	$5,0 \times 10^{-5} \times U$			
	300 kHz	$12 \times 10^{-5} \times U$			
	500 kHz	$25 \times 10^{-5} \times U$			
	1 MHz	$60 \times 10^{-5} \times U$			
10 V	10 Hz to 30 Hz	$4,0 \times 10^{-5} \times U$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 30 kHz	$3,0 \times 10^{-5} \times U$			
	50 kHz	$3,5 \times 10^{-5} \times U$			
	100 kHz	$4,0 \times 10^{-5} \times U$			
	300 kHz	$11 \times 10^{-5} \times U$			
	500 kHz	$22 \times 10^{-5} \times U$			
	1 MHz	$60 \times 10^{-5} \times U$			
19 V	1 kHz	$4,0 \times 10^{-5} \times U$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
100 V	10 Hz to 30 Hz	$4,5 \times 10^{-5} \times U$			
	40 Hz & 55 Hz	$4,0 \times 10^{-5} \times U$			
	300 Hz to 20 kHz	$3,0 \times 10^{-5} \times U$			
	30 kHz	$3,5 \times 10^{-5} \times U$			
	50 kHz	$4,5 \times 10^{-5} \times U$			
	100 kHz	$7,4 \times 10^{-5} \times U$			
	40 Hz to 1 kHz	$4,0 \times 10^{-5} \times U$			
1000 V	10 kHz	$4,5 \times 10^{-5} \times U$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS
	20 kHz	$5,0 \times 10^{-5} \times U$			
	30 kHz	$7,5 \times 10^{-5} \times U$			
	50 kHz	$13 \times 10^{-5} \times U$			
700 V	100 kHz	$35 \times 10^{-5} \times U$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>measuring</li> </ul>	P2-02-E.006	AN, OS

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0,7 mV to 2,2 mV	10 Hz to 20 Hz	$17 \times 10^{-4} \times U + 1,3 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$7,4 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	40 Hz to 20 kHz	$4,2 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	20 kHz to 50 kHz	$8,2 \times 10^{-4} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$12 \times 10^{-4} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$23 \times 10^{-4} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$26 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$50 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
2 mV to 7 mV	10 Hz to 20 Hz	$8,5 \times 10^{-4} \times U + 1,3 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$3,7 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	40 Hz to 20 kHz	$2,1 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	20 kHz to 50 kHz	$4,1 \times 10^{-4} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$6,1 \times 10^{-4} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$12 \times 10^{-4} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$14 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$36 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
7 mV to 22 mV	10 Hz to 20 Hz	$2,9 \times 10^{-4} \times U + 1,3 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$1,9 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	40 Hz to 20 kHz	$1,1 \times 10^{-4} \times U + 1,3 \mu\text{V}$			
	20 kHz to 50 kHz	$2,1 \times 10^{-4} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$3,1 \times 10^{-4} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$8,2 \times 10^{-4} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$10 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$26 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
22 mV to 70 mV	10 Hz to 20 Hz	$2,4 \times 10^{-4} \times U + 1,5 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$1,3 \times 10^{-4} \times U + 1,5 \mu\text{V}$			
	40 Hz to 20 kHz	$0,69 \times 10^{-4} \times U + 1,5 \mu\text{V}$			
	20 kHz to 50 kHz	$1,3 \times 10^{-4} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$2,6 \times 10^{-4} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$5,3 \times 10^{-4} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$6,8 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$13 \times 10^{-4} \times U + 8,0 \mu\text{V}$			
70 mV to 220 mV	10 Hz to 20 Hz	$21 \times 10^{-5} \times U + 1,5 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$8,7 \times 10^{-5} \times U + 1,5 \mu\text{V}$			
	40 Hz to 20 kHz	$4,3 \times 10^{-5} \times U + 1,5 \mu\text{V}$			
	20 kHz to 50 kHz	$7,3 \times 10^{-5} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$16 \times 10^{-5} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$28 \times 10^{-5} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$40 \times 10^{-5} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$120 \times 10^{-5} \times U + 8,0 \mu\text{V}$			
220 mV to 700 mV	10 Hz to 20 Hz	$21 \times 10^{-5} \times U + 1,5 \mu\text{V}$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$8,7 \times 10^{-5} \times U + 1,5 \mu\text{V}$			
	40 Hz to 20 kHz	$3,8 \times 10^{-5} \times U + 1,5 \mu\text{V}$			
	20 kHz to 50 kHz	$5,6 \times 10^{-5} \times U + 2,0 \mu\text{V}$			
	50 kHz to 100 kHz	$8,4 \times 10^{-5} \times U + 2,5 \mu\text{V}$			
	100 kHz to 300 kHz	$21 \times 10^{-5} \times U + 4,0 \mu\text{V}$			
	300 kHz to 500 kHz	$34 \times 10^{-5} \times U + 8,0 \mu\text{V}$			
	500 kHz to 1 MHz	$120 \times 10^{-5} \times U + 8,0 \mu\text{V}$			
0,7 V to 2,2 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$6,9 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$2,9 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$5,2 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$7,6 \times 10^{-5} \times U$			
	100 kHz to 300 kHz	$20 \times 10^{-5} \times U$			
	300 kHz to 500 kHz	$31 \times 10^{-5} \times U$			
	500 kHz to 1 MHz	$120 \times 10^{-5} \times U$			

2,2 V to 7 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$7,0 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$2,9 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$5,3 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$8,8 \times 10^{-5} \times U$			
	100 kHz to 300 kHz	$22 \times 10^{-5} \times U$			
	300 kHz to 500 kHz	$47 \times 10^{-5} \times U$			
	500 kHz to 1 MHz	$150 \times 10^{-5} \times U$			
7 V to 22 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$7,0 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$3,1 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$5,3 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$8,5 \times 10^{-5} \times U$			
	100 kHz to 300 kHz	$22 \times 10^{-5} \times U$			
	300 kHz to 500 kHz	$47 \times 10^{-5} \times U$			
	500 kHz to 1 MHz	$150 \times 10^{-5} \times U$			
22 V to 70 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$7,2 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$3,9 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$6,3 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$11 \times 10^{-5} \times U$			
	100 kHz to 300 kHz	$22 \times 10^{-5} \times U$			
	300 kHz to 500 kHz	$51 \times 10^{-5} \times U$			
	500 kHz to 1 MHz	$150 \times 10^{-5} \times U$			
70 V to 220 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$7,2 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$3,8 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$7,7 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$11 \times 10^{-5} \times U$			
	100 kHz to 300 kHz	$26 \times 10^{-5} \times U$			
	300 kHz to 500 kHz	$70 \times 10^{-5} \times U$			
	500 kHz to 1 MHz	$150 \times 10^{-5} \times U$			
220 V to 700 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$11 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$4,7 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$15 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$85 \times 10^{-5} \times U$			
700 V to 1000 V	10 Hz to 20 Hz	$7 \times 10^{-5} \times U$	• measure	P2-02-E.019	AN, OS
	20 Hz to 40 Hz	$11 \times 10^{-5} \times U$			
	40 Hz to 20 kHz	$4,4 \times 10^{-5} \times U$			
	20 kHz to 50 kHz	$15 \times 10^{-5} \times U$			
	50 kHz to 100 kHz	$85 \times 10^{-5} \times U$			
1 kV to 53 kV	50 / 60 Hz	$3,0 \times 10^{-3} \times U$	• measure	P2-02-E.016	AN, OS

## Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
2 mV to 20 mV	1 kHz to 10 kHz	$7,0 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	10 kHz to 100 kHz	$11 \times 10^{-4} \times U$			
20 mV to 200 mV	10 Hz to 300 Hz	$2,1 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	300 Hz to 10 kHz	$1,8 \times 10^{-4} \times U$			
	10 kHz to 30 kHz	$2,8 \times 10^{-4} \times U$			
	30 kHz to 100 kHz	$6,1 \times 10^{-4} \times U$			
0,2 V to 2 V	10 Hz to 300 Hz	$1,6 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	300 Hz to 1 kHz	$1,1 \times 10^{-4} \times U$			
	1 kHz to 30 kHz	$0,70 \times 10^{-4} \times U$			
	30 kHz to 100 kHz	$1,6 \times 10^{-4} \times U$			
	100 kHz to 300 kHz	$6,0 \times 10^{-4} \times U$			
	300 kHz to 1 MHz	$30 \times 10^{-4} \times U$			
2 V to 20 V	10 Hz to 300 Hz	$1,6 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	300 Hz to 1 kHz	$1,0 \times 10^{-4} \times U$			
	1 kHz to 10 kHz	$0,80 \times 10^{-4} \times U$			
	10 kHz to 30 kHz	$0,70 \times 10^{-4} \times U$			
	30 kHz to 100 kHz	$1,7 \times 10^{-4} \times U$			
	100 kHz to 300 kHz	$6,0 \times 10^{-4} \times U$			
	300 kHz to 1 MHz	$30 \times 10^{-4} \times U$			
20 V to 200 V	10 Hz to 300 Hz	$1,6 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	300 Hz to 1 kHz	$1,2 \times 10^{-4} \times U$			
	1 kHz to 10 kHz	$1,0 \times 10^{-4} \times U$			
	10 kHz to 30 kHz	$1,1 \times 10^{-4} \times U$			
	30 kHz to 100 kHz	$2,1 \times 10^{-4} \times U$			
200 V to 1000 V	40 Hz to 300 Hz	$2,3 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
	300 Hz to 1 kHz	$2,3 \times 10^{-4} \times U$			
	1 kHz to 10 kHz	$1,7 \times 10^{-4} \times U$			
	10 kHz to 30 kHz	$2,2 \times 10^{-4} \times U$			
200 V to 750 V	30 kHz to 100 kHz	$15 \times 10^{-4} \times U$	• generate	P2-02-E.005	AN, OS
1 kV to 45 kV	50 / 60 Hz	$3,0 \times 10^{-3} \times U$	• generate	P2-02-E.016	AN, OS

Alternating current  
Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
100 µA	10 Hz to 30 Hz	$1,4 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 1 kHz	$1,1 \times 10^{-4} \times I$			
	5 kHz	$1,7 \times 10^{-4} \times I$			
1 mA	10 Hz to 30 Hz	$1,3 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 1 kHz	$1,0 \times 10^{-4} \times I$			
	5 kHz	$1,5 \times 10^{-4} \times I$			
10 mA	10 Hz to 30 Hz	$1,3 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 1 kHz	$1,0 \times 10^{-4} \times I$			
	5 kHz	$1,5 \times 10^{-4} \times I$			
100 mA	10 Hz to 30 Hz	$1,3 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 1 kHz	$1,0 \times 10^{-4} \times I$			
	5 kHz	$1,5 \times 10^{-4} \times I$			
1 A	10 Hz to 30 Hz	$1,8 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>Measurement</li> </ul>	P2-02-E.006	AN, OS
	40 Hz to 1 kHz	$1,2 \times 10^{-4} \times I$			
	5 kHz	$2,3 \times 10^{-4} \times I$			
10 A	40 Hz	$3,0 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	50 Hz to 1 kHz	$2,9 \times 10^{-4} \times I$			
	5 kHz	$4,0 \times 10^{-4} \times I$			
	10 kHz	$7,0 \times 10^{-4} \times I$			
Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
10 mA	10 Hz to 300 Hz	$61 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	300 Hz to 5 kHz	$35 \times 10^{-6} \times I$			
	5 kHz to 10 kHz	$41 \times 10^{-6} \times I$			
100 mA	10 kHz to 30 kHz	$45 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	10 Hz to 300 Hz	$66 \times 10^{-6} \times I$			
	300 Hz to 5 kHz	$37 \times 10^{-6} \times I$			
1A	5 kHz to 10 kHz	$41 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	10 kHz to 30 kHz	$45 \times 10^{-6} \times I$			
	10 Hz to 300 Hz	$70 \times 10^{-6} \times I$			
10A	300 Hz to 5 kHz	$49 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	5 kHz to 10 kHz	$51 \times 10^{-6} \times I$			
	10 kHz to 30 kHz	$55 \times 10^{-6} \times I$			
20A	10 Hz to 300 Hz	$101 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	300 Hz to 5 kHz	$88 \times 10^{-6} \times I$			
	5 kHz to 10 kHz	$90 \times 10^{-6} \times I$			
50A	10 kHz to 30 kHz	$95 \times 10^{-6} \times I$	<ul style="list-style-type: none"> <li>measure / generate</li> <li>AC/DC difference</li> </ul>	P2-02-E.022	AN
	10 Hz to 300 Hz	$101 \times 10^{-6} \times I$			
	300 Hz to 5 kHz	$88 \times 10^{-6} \times I$			
5 µA to 200 µA	5 kHz to 10 kHz	$5,0 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure</li> </ul>	P2-02-E.019	AN, OS
	10 Hz to 5 kHz	$1,6 \times 10^{-4} \times I$			
	5 kHz to 10 kHz	$0,60 \times 10^{-4} \times I$			
0,2 mA to 2 mA	10 Hz to 5 kHz	$1,3 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure</li> </ul>	P2-02-E.019	AN, OS
	5 kHz to 10 kHz	$1,0 \times 10^{-4} \times I$			
	10 Hz to 5 kHz	$5,0 \times 10^{-4} \times I$			
2 mA to 20 mA	10 Hz to 5 kHz	$1,0 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure</li> </ul>	P2-02-E.019	AN, OS
	5 kHz to 10 kHz	$26 \times 10^{-4} \times I$			
	10 Hz to 1 kHz	$1,0 \times 10^{-4} \times I$			
0,2 A to 2 A	1 kHz to 10 kHz	$4,0 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure</li> </ul>	P2-02-E.019	AN, OS
	10 Hz to 1 kHz	$1,0 \times 10^{-4} \times I$			
	1 kHz to 10 kHz	$3,0 \times 10^{-4} \times I$			
2 A to 20 A	10 Hz to 1 kHz	$10 \times 10^{-4} \times I$	<ul style="list-style-type: none"> <li>measure</li> </ul>	P2-02-E.019	AN, OS
	1 kHz to 5 kHz	$3,0 \times 10^{-4} \times I$			
	5 kHz to 10 kHz	$10 \times 10^{-4} \times I$			

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
20 A to 6000 A	50 / 60 Hz	$5,0 \times 10^{-4} \times I$	measure	P2-02-E.030	AN, OS
20 A to 4000 A	50 / 60 Hz	$5,0 \times 10^{-4} \times I$	generate	P2-02-E.030	AN, OS

Calibration of current clamps

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
20 A to 1000 A	45 Hz to 440 Hz	$5,0 \times 10^{-3} \times I$	• with current coils	P2-02-E.022	AN, OS

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
20 µA to 200 µA	10 Hz to 1 kHz	$4,0 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$6,0 \times 10^{-4} \times I$			
0,2 mA to 2 mA	10 Hz to 1 kHz	$3,2 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$4,0 \times 10^{-4} \times I$			
2 mA to 20 mA	10 Hz to 1 kHz	$3,1 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$4,1 \times 10^{-4} \times I$			
20 mA to 200 mA	10 Hz to 1 kHz	$3,1 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$4,0 \times 10^{-4} \times I$			
0,2 A to 2 A	10 Hz to 1 kHz	$6,0 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$7,1 \times 10^{-4} \times I$			
2 A to 10 A	10 Hz to 1 kHz	$6,1 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	1 kHz to 5 kHz	$12 \times 10^{-4} \times I$			
	5 kHz to 10 kHz	$34 \times 10^{-4} \times I$			
10 A to 20 A	45 Hz to 100 Hz	$17 \times 10^{-4} \times I$	• generate • in the lowest range possible	P2-02-E.005	AN, OS
	100 Hz to 1 kHz	$20 \times 10^{-4} \times I$			

Power and Energy

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
Mono phase , direct without measuring clamps					
33 mV to 1000 V / 0,33 mA to 330 mA	DC	$3,0 \times 10^{-4} \times P$	11 µW to 330 W generate	P2-02-E.013	AN, OS
33 mV to 1000 V / 0,33 A to 3,3 A	DC	$5,0 \times 10^{-4} \times P$	3,3 kW generate		
33 mV to 1000 V / 3,3 A to 10,5 A	DC	$6,0 \times 10^{-4} \times P$	10,5 kW generate		
33 mV to 1000 V / 10,5 A to 20,5 A	DC	$11 \times 10^{-4} \times P$	20,5 kW generate		
33 mV to 1000 V / 0,1 mA to 20,5A	45 Hz to 1 kHz	$15 \times 10^{-4} \times P$	3,3 µW to 20,5 kW / kVA(r) generate cosphi/sinphi > 0,5		
33 mV to 1000 V / 0,1 mA to 20,5A	45 Hz to 1 kHz	$40 \times 10^{-4} \times P$	3,3 µW to 20,5 kW / kVA(r) generate cosphi/sinphi > 0,25		
Mono phase , direct with measuring clamps					
33 mV to 1000 V / 20 A to 500 A	DC	$10 \times 10^{-3} \times P$	0,66 W to 500 kW / kVA(r) generate	P2-02-E.013 P2-02-E.022	AN, OS
33 mV to 1000 V / 20 A to 500 A	45 Hz to 100 Hz	$11 \times 10^{-3} \times P$	0,66 W to 500 kW / kVA(r) generate cosphi/sinphi > 0,25		
33 mV to 1000 V / 20 A to 500 A	100 Hz to 440 Hz	$16 \times 10^{-3} \times P$	0,66 W to 500 kW / kVA(r) generate cosphi/sinphi > 0,25		

3-phase, direct without measuring clamps					
1 V to 300 V / 0,3 A to 100 A	50 Hz & 60 Hz	$2,0 \times 10^{-3} \times P$	0,3 W to 30 kW / kVA(r) generate cosphi/sinphi > 0,5	P2-02-E.018	AN
1 V to 300 V / 0,3 A to 100 A	50 Hz & 60 Hz	$4,0 \times 10^{-3} \times P$	0,3 W to 30 kW / kVA(r) generate cosphi/sinphi > 0,25		
1 V to 1000 V / 0,3 A to 100 A	10 Hz to 1 kHz	$2,0 \times 10^{-3} \times P$	0,3 W to 100 kW / kVA(r) measure cosphi/sinphi > 0,5		
1 V to 1000 V / 0,3 A to 100 A	10 Hz to 1 kHz	$4,0 \times 10^{-3} \times P$	0,3 W to 100 kW / kVA(r) measure cosphi/sinphi > 0,25		
3-phase, direct with measuring clamps					
1 V to 300 V / 20 A to 500 A	50 Hz & 60 Hz	$11 \times 10^{-3} \times P$	20 W to 150 kW / kVA(r) generate cosphi/sinphi > 0,25	P2-02-E.013 P2-02-E.022	AN, OS
1 V to 1000 V / 20 A to 100 A	15 Hz to 440 Hz	$16 \times 10^{-3} \times P$	20 W to 100 kW / kVA(r) measure cosphi/sinphi > 0,25		
Phase / phase angle					
Cosphi/sinphi -1 to 1	10 Hz to 1 kHz	0,000 40	measure / generate	P2-02-E.018	AN, OS
Phase angle -180 to 180 °	10 Hz to 1 kHz	0,02°	measure / generate		

P indicates active/reactive as well as apparent power.

#### RF Power

Range amplitude	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
-67 dBm to -19 dBm	20 kHz to 100 MHz	0,056 dB	• measure	P2-02-E.036	AN
	100 MHz to 4 GHz	0,047 dB			
-19 dBm to 1 dBm	20 kHz to 100 MHz	0,066 dB	• measure	P2-02-E.036	AN
	100 MHz to 4 GHz	0,058 dB			
1 dBm to 23 dBm	20 kHz to 100 MHz	0,083 dB	• measure	P2-02-E.036	AN
	100 MHz to 4 GHz	0,072 dB			
24 dBm to 20 dBm	10 Hz to 20 kHz	0,050 dB	• generate	P2-02-E.035	AN
	20 kHz to 100 kHz	0,050 dB			
	100 kHz to 10 MHz	0,050 dB			
	10 MHz to 125 MHz	0,050 dB			
20 dBm to 14 dBm	10 Hz to 20 kHz	0,050 dB	• generate	P2-02-E.035	AN
	20 kHz to 100 kHz	0,050 dB			
	100 kHz to 10 MHz	0,050 dB			
	10 MHz to 125 MHz	0,050 dB			
	125 MHz to 300 MHz	0,10 dB			
	300 MHz to 1,4 GHz	0,25 dB			
14 dBm to -17 dBm	10 Hz to 20 kHz	0,050 dB	• generate	P2-02-E.035	AN
	20 kHz to 100 kHz	0,050 dB			
	100 kHz to 10 MHz	0,050 dB			
	10 MHz to 125 MHz	0,050 dB			
	125 MHz to 300 MHz	0,10 dB			
	300 MHz to 1,4 GHz	0,25 dB			
	1,4 GHz to 3 GHz	0,30 dB			
	3 GHz to 4 GHz	0,50 dB			

-17 dBm to -48 dBm	10 Hz to 20 kHz	0,050 dB	• generate	P2-02-E.035	AN
	20 kHz to 100 kHz	0,050 dB			
	100 kHz to 10 MHz	0,050 dB			
	10 MHz to 125 MHz	0,050 dB			
	125 MHz to 300 MHz	0,10 dB			
	300 MHz to 1,4 GHz	0,50 dB			
	1,4 GHz to 3 GHz	0,50 dB			
	3 GHz to 4 GHz	0,50 dB			
-48 dBm to -74 dBm	100 kHz to 10 MHz	0,20 dB	• generate	P2-02-E.035	AN
	10 MHz to 125 MHz	0,20 dB			
	125 MHz to 300 MHz	0,20 dB			
	300 MHz to 1,4 GHz	0,50 dB			
	1,4 GHz to 3 GHz	0,50 dB			
	3 GHz to 4 GHz	0,50 dB			
-74 dBm to -84 dBm	100 kHz to 10 MHz	0,50 dB	• generate	P2-02-E.035	AN
	10 MHz to 125 MHz	0,50 dB			
	125 MHz to 300 MHz	0,50 dB			
	300 MHz to 1,4 GHz	1,0 dB			
	1,4 GHz to 3 GHz	1,0 dB			
	3 GHz to 4 GHz	1,0 dB			
-84 dBm to -94 dBm	100 kHz to 10 MHz	0,50 dB	• generate	P2-02-E.035	AN
	10 MHz to 125 MHz	0,50 dB			
	125 MHz to 300 MHz	0,50 dB			
	300 MHz to 1,4 GHz	1,0 dB			
	1,4 GHz to 3 GHz	1,0 dB			
-94 dBm to -124 dBm	100 kHz to 10 MHz	1,5 dB	• generate	P2-02-E.035	AN
	10 MHz to 125 MHz	1,5 dB			
	125 MHz to 300 MHz	1,5 dB			
	300 MHz to 1,4 GHz	1,5 dB			
	1,4 GHz to 3 GHz	1,5 dB			

Impedance (DC/LF)

Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
1 Ω	DC	$11 \times 10^{-6} \times R$	<ul style="list-style-type: none"> <li>Transfer standard in "30 day" loop</li> <li>Fixed points</li> <li>• Measuring</li> <li>• 4-wire resistance measurement</li> <li>• Negligible dissipated power</li> </ul>	P2-02-E.006	AN, OS
10 Ω	DC	$9,5 \times 10^{-6} \times R$			
100 Ω	DC	$6,5 \times 10^{-6} \times R$			
1 kΩ	DC	$4,5 \times 10^{-6} \times R$			
10 kΩ	DC	$4,5 \times 10^{-6} \times R$			
100 kΩ	DC	$7,5 \times 10^{-6} \times R$			
1 MΩ	DC	$1,4 \times 10^{-5} \times R$			
10 MΩ	DC	$2,5 \times 10^{-5} \times R$			
100 MΩ	DC	$2,0 \times 10^{-4} \times R$			
Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 Ω to 2 Ω	DC	$18 \times 10^{-6} \times R$ or $20 \mu\Omega^1$	<ul style="list-style-type: none"> <li>measure</li> <li>• 4-wire resistance measurement</li> <li>• negligible dissipated power</li> </ul>	P2-02-E.019	AN, OS
2 Ω to 20 Ω	DC	$3,1 \times 10^{-6} \times R$			
20 Ω to 200 Ω	DC	$5,5 \times 10^{-6} \times R$			
0,2 kΩ to 2 kΩ	DC	$2,6 \times 10^{-6} \times R$			
2 kΩ to 20 kΩ	DC	$5,0 \times 10^{-6} \times R$			
20 kΩ to 200 kΩ	DC	$6,3 \times 10^{-6} \times R$			
0,2 MΩ to 2 MΩ	DC	$6,0 \times 10^{-6} \times R$			
2 MΩ to 20 MΩ	DC	$11 \times 10^{-6} \times R$			
20 MΩ to 200 MΩ	DC	$60 \times 10^{-6} \times R$			
0,2 GΩ to 2 GΩ	DC	$1,2 \times 10^{-3} \times R$			

<sup>1</sup> Whichever is greater

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
0 Ω	DC	$100 \mu\Omega$	<ul style="list-style-type: none"> <li>generate</li> <li>standard resistors</li> <li>also combinations of these resistors<sup>1</sup></li> <li>• 4-wire resistance</li> <li>• maximum dissipated power <math>10 \text{ mW}^{1,2}</math></li> </ul>	P2-02-E.020	AN
1 mΩ	DC	$12 \times 10^{-6} \times R$			
10 mΩ	DC	$12 \times 10^{-7} \times R$			
100 mΩ	DC	$3 \times 10^{-6} \times R$			
1 Ω	DC	$12 \times 10^{-7} \times R$			
10 Ω, 25 Ω, 100 Ω, 1 kΩ, 10 kΩ, 100 kΩ	DC	$5 \times 10^{-7} \times R$			
1 MΩ	DC	$15 \times 10^{-7} \times R$			
10 MΩ	DC	$8 \times 10^{-6} \times R$			
100 MΩ	DC	$2 \times 10^{-5} \times R$			
1 GΩ	DC	$7 \times 10^{-5} \times R$			
10 GΩ	DC	$3 \times 10^{-4} \times R$			
100 GΩ	DC	$1 \times 10^{-3} \times R$			
1 TΩ	DC	$2 \times 10^{-3} \times R$			
10 TΩ	DC	$6 \times 10^{-3} \times R$			
100 TΩ	DC	$2 \times 10^{-2} \times R$			
378 Ω	DC	$4 \times 10^{-6} \times R$			
10 Ω	75 Hz	$3,0 \times 10^{-6} \times R$	<ul style="list-style-type: none"> <li>generate</li> <li>standard resistors</li> <li>also combinations of these resistors<sup>1</sup></li> <li>• 4-wire resistance</li> </ul>	P2-02-E.020	AN
25 Ω	75 Hz	$1,5 \times 10^{-6} \times R$			
100 Ω	75 Hz	$1,5 \times 10^{-6} \times R$			
378 Ω	75 Hz	$3,0 \times 10^{-6} \times R$			

<sup>1</sup> The uncertainty varies as the combinations and the dissipated power are different.

<sup>2</sup> these resistors can be used to generate/measure currents from 10pA up to 10A with decreased uncertainties.

Calibration of resistor / insulation  
meters

Measuring range or point	@Voltage range	expanded uncertainty (*)	Remark	Calibration procedure	
10 kΩ to 40 MΩ	50 V to 250 V	$1,0 \times 10^{-4} \times R$		RP/02/KC/E.17	AN, OS
40 MΩ to 200 MΩ		$5,0 \times 10^{-4} \times R$			
100 kΩ to 200 MΩ		$1,0 \times 10^{-4} \times R$			
200 MΩ to 1000 MΩ		$3,0 \times 10^{-4} \times R$			
1 MΩ to 10 GΩ		$60 \times 10^{-4} \times R$			

Capacity

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
10 pF to 100 pF	1 kHz	$15 \times 10^{-4} \times C$	Measure / generate	P2-02-E.010	AN
100 pF to 1000 nF	1 kHz	$10 \times 10^{-4} \times C$	Measure / generate		
1000 nF to 10 µF	100 Hz & 1 kHz	$6 \times 10^{-4} \times C$	Measure / generate		
10 µF tot 100 µF	100 Hz & 1 kHz	$7 \times 10^{-4} \times C$	Measure / generate		
10 pF, 100 pF, 1 nF, 10 nF	1 kHz	$1,0 \times 10^{-4} \times C$	Generate	P2-02-E.040	AN
100 nF, 1 µF	1 kHz	$1,5 \times 10^{-4} \times C$			
10 µF	1 kHz	$3,0 \times 10^{-4} \times C$			
100 µF	1 kHz	$5,0 \times 10^{-4} \times C$			
1 µF	100 Hz	$2,0 \times 10^{-4} \times C$			
10 µF	100 Hz	$3,0 \times 10^{-4} \times C$			
100 µF	100 Hz	$5,0 \times 10^{-4} \times C$			

Inductance

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	calibration/procedure	
100 µH to 1 H	1 kHz	$10 \times 10^{-4} \times L$	Measure / generate	P2-02-E.010	AN
1 H to 10 H	1 kHz	$20 \times 10^{-4} \times L$	Measure / generate		
100 µH, 1 mH, 10 mH, 100 mH, 1H	1 kHz	$5,0 \times 10^{-4} \times L$	Generate	P2-02-E.040	AN
10 H	100 Hz, 1 kHz	$7,0 \times 10^{-4} \times L$			

Oscilloscopes (on screen) – input  
impedance 50 Ω and 1 MΩ

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure			
± 1 mV to 200 V	DC	$2,5 \times 10^{-4} \times U + 25 \mu\text{V}$	50 Ω to 5,56 V				
1 mVpp to 21 mVpp	10 Hz to 10 kHz	$25 \times 10^{-4} \times U + 10 \mu\text{V}$	Square wave				
21 mVpp to 556 mVpp	10 Hz to 10 kHz	$10 \times 10^{-4} \times U + 10 \mu\text{V}$	Square wave				
556 mVpp to 210 Vpp	10 Hz to 10 kHz	$5,0 \times 10^{-4} \times U + 10 \mu\text{V}$	Square wave 50 Ω to 5,56 V				
4,44 mVpp to 5,56 Vpp	100 mHz to 100 MHz	$1,5 \times 10^{-2} \times U$	Sine wave				
4,44 mVpp to 5,56 Vpp	100 MHz to 550 MHz	$3,0 \times 10^{-2} \times U$	Sine wave				
4,44 mVpp to 3,35 Vpp	550 MHz to 1 GHz	$4,0 \times 10^{-2} \times U$	Sine wave				
4,44 mVpp to 3,54 Vpp	1 GHz to 4 GHz	$6,0 \times 10^{-2} \times U$	Sine wave				
500 ps	-	40 ps	Rise/ falltime (max. 3 V)				
250 ps to 10 ks	-	$5,0 \times 10^{-9} \times t$	Time base				
40 Ω to 90 Ω	1 kHz	$1,0 \times 10^{-3} \times Z$	Input impedance	P2-02-E.007	AN, OS		
0,8 MΩ to 1,2 MΩ							
10 Ω to 150 Ω	1 kHz	$5,0 \times 10^{-3} \times Z$	Input impedance				
50 kΩ to 12 MΩ							
	0,1 Hz to 100 MHz	0,15 dB	Attenuation at bandwidth				
	100 MHz to 550 MHz	0,30 dB	Attenuation at bandwidth				
	550 MHz to 1 GHz	0,40 dB	Attenuation at bandwidth				
	1 GHz to 4 GHz	0,50 dB	Attenuation at bandwidth	P2-02-E.035	AN, OS		

#### Bridge calibration

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure	
-2,5 mV / V to 2,5 mV / V	225 Hz	$50 \times 10^{-6} \text{ mV} / \text{V}$	5 V supply / 350 Ω bridges		AN, OS

(\*) the smallest uncertainty of measurement the laboratory can provide to its customers, expressed as the expanded uncertainty having a coverage probability of approximately 95%.

**DCLF Electricity Wellin**  
**Calibration and Measurement Capabilities**

Direct voltage  
Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 mV to 200 mV	DC	$5,0 \times 10^{-6} \times U + 2,0 \mu\text{V}$	• measure • positive / negative	P2-02-E.019.C
0,2 V to 2 V	DC	$5,0 \times 10^{-6} \times U + 2,0 \mu\text{V}$		
2 V to 20 V	DC	$5,0 \times 10^{-6} \times U + 5,0 \mu\text{V}$		
20 V to 200 V	DC	$5,5 \times 10^{-6} \times U + 60 \mu\text{V}$		
200 V to 1000 V	DC	$10,0 \times 10^{-6} \times U + 550 \mu\text{V}$		

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 mV to 220 mV	DC	$8,0 \times 10^{-6} \times U + 2,0 \mu\text{V}$	• generate • positive / negative	P2-02-E.039.C
220 mV to 2,2 V	DC	$8,0 \times 10^{-6} \times U + 2,0 \mu\text{V}$		
2,2 V to 22 V	DC	$8,0 \times 10^{-6} \times U + 6,5 \mu\text{V}$		
22 V to 220 V	DC	$9,0 \times 10^{-6} \times U + 80 \mu\text{V}$		
220 V to 1100 V	DC	$11 \times 10^{-6} \times U + 500 \mu\text{V}$		

Direct current

Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 µA to 200 µA	DC	$12 \times 10^{-6} \times I + 1,0 \text{nA}$	• measure • in the lowest possible range • positive / negative	P2-02-E.019.C
0,2 mA to 2,0 mA	DC	$12 \times 10^{-6} \times I + 6,0 \text{nA}$		
2,0 mA to 20 mA	DC	$15 \times 10^{-6} \times I + 50 \text{nA}$		
20 mA to 200 mA	DC	$55 \times 10^{-6} \times I + 2,5 \mu\text{A}$		
0,2 A to 2 A	DC	$20 \times 10^{-5} \times I + 20 \mu\text{A}$		
2 A to 20 A	DC	$41 \times 10^{-5} \times I + 450 \mu\text{A}$		
10 A to 100 A	DC	$2 \times 10^{-5} \times I + 2 \text{mA}$		P2-02-E.058

Calibration of current clamps

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
20 A to 1000 A	DC	$5,0 \times 10^{-3} \times I$	• with current coils	P2-02-E.021

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 µA to 2,2 mA	DC	$55 \times 10^{-6} \times I + 8,0 \text{nA}$	• generate • positive / negative	P2-02-E.039.C
2,2 mA to 22 mA	DC	$55 \times 10^{-6} \times I + 80 \text{nA}$		
22 mA to 220 mA	DC	$90 \times 10^{-6} \times I + 1,0 \mu\text{A}$		
220 mA to 2,2 A	DC	$12 \times 10^{-5} \times I + 30 \mu\text{A}$		
2,2 A to 11 A	DC	$38 \times 10^{-5} \times I + 490 \mu\text{A}$		
2 A to 20 A	DC	$1 \times 10^{-5} \times I + 0,3 \text{mA}$		
20 A to 100 A	DC	$2 \times 10^{-5} \times I + 2 \text{mA}$		P2-02-E.058

Alternating voltage

Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
10 mV to 200 mV	20 Hz to 10 kHz	$14 \times 10^{-5} \times U + 5,0 \mu V$	• measure	P2-02-E.019.C
	10 kHz to 30 kHz	$35 \times 10^{-5} \times U + 10 \mu V$		
	30 kHz to 100 kHz	$77 \times 10^{-5} \times U + 22 \mu V$		
200 mV to 2 V	20 Hz to 10 kHz	$12 \times 10^{-5} \times U + 25 \mu V$	• measure	P2-02-E.019.C
	10 kHz to 30 kHz	$25 \times 10^{-5} \times U + 50 \mu V$		
	30 kHz to 100 kHz	$57 \times 10^{-5} \times U + 210 \mu V$		
2 V to 20 V	20 Hz to 10 kHz	$12 \times 10^{-5} \times U + 200 \mu V$	• measure	P2-02-E.019.C
	10 kHz to 30 kHz	$25 \times 10^{-5} \times U + 400 \mu V$		
	30 kHz to 100 kHz	$58 \times 10^{-5} \times U + 2000 \mu V$		
20 V to 200 V	20 Hz to 10 kHz	$12 \times 10^{-5} \times U + 2,0 \text{ mV}$	• measure	P2-02-E.019.C
	10 kHz to 30 kHz	$22 \times 10^{-5} \times U + 5,0 \text{ mV}$		
	30 kHz to 100 kHz	$57 \times 10^{-5} \times U + 22 \text{ mV}$		
200 V to 1000 V	50 Hz to 10 kHz	$30 \times 10^{-5} \times U + 50 \text{ mV}$	• measure	P2-02-E.019.C
	10 kHz to 30 kHz	$15 \times 10^{-4} \times U + 50 \text{ mV}$		

Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
2,2 mV to 22 mV	20 Hz to 20 kHz	$13 \times 10^{-5} \times U + 6,0 \mu V$	• generate	P2-02-E.039.C
	20 kHz to 100 kHz	$87 \times 10^{-5} \times U + 30 \mu V$		
22 mV to 220 mV	20 Hz to 20 kHz	$13 \times 10^{-5} \times U + 9,0 \mu V$	• generate	P2-02-E.039.C
	20 kHz to 100 kHz	$88 \times 10^{-5} \times U + 30 \mu V$		
0,22 V to 2,2 V	20 Hz to 20 kHz	$10 \times 10^{-5} \times U + 10 \mu V$	• generate	P2-02-E.039.C
	20 kHz to 100 kHz	$26 \times 10^{-5} \times U + 90 \mu V$		
2,2 V to 22 V	40 Hz to 20 kHz	$11 \times 10^{-5} \times U + 70 \mu V$	• generate	P2-02-E.039.C
	20 kHz to 100 kHz	$28 \times 10^{-5} \times U + 360 \mu V$		
22 V to 220 V	40 Hz to 20 kHz	$11 \times 10^{-5} \times U + 1,0 \text{ mV}$	• generate	P2-02-E.039.C
	20 kHz to 100 kHz	$52 \times 10^{-5} \times U + 10 \text{ mV}$		
220 V to 1100 V	50 Hz to 1 kHz	$11 \times 10^{-5} \times U + 5,0 \text{ mV}$	• generate	P2-02-E.039.C
	1 kHz to 20 kHz	$18 \times 10^{-5} \times U + 8,0 \text{ mV}$		

Alternating current

Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
10 µA to 200 µA	55 Hz to 5 kHz	$31 \times 10^{-5} \times I + 40 \text{ nA}$	• measure	P2-02-E.019.C
0,2 mA to 2 mA	50 Hz to 5 kHz	$31 \times 10^{-5} \times I + 400 \text{ nA}$		
2 mA to 20 mA	50 Hz to 5 kHz	$31 \times 10^{-5} \times I + 2,5 \mu A$		
20 mA to 200 mA	50 Hz to 5 kHz	$30 \times 10^{-5} \times I + 25 \mu A$		
0,2 A to 2 A	50 Hz to 1 kHz	$63 \times 10^{-5} \times I + 25 \mu A$		
	1 kHz to 5 kHz	$73 \times 10^{-5} \times I + 25 \mu A$		
2 A to 20 A	50 Hz to 1 kHz	$85 \times 10^{-5} \times I + 250 \mu A$		

Calibration of current clamps

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
20 A to 1000 A	45 Hz to 440 Hz	$5,0 \times 10^{-3} \times I$	• with current coils	P2-02-E.021

## Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
10 µA to 220 µA	40 Hz to 1 kHz	$14 \times 10^{-5} \times I + 35 \text{ nA}$	• generate	P2-02-E.039.C
220 µA to 2,2 mA	40 Hz to 1 kHz	$20 \times 10^{-5} \times I + 35 \text{ nA}$		
2,2 mA to 22 mA	40 Hz to 1 kHz	$20 \times 10^{-5} \times I + 350 \text{ nA}$		
22 mA to 220 mA	40 Hz to 1 kHz	$20 \times 10^{-5} \times I + 3,5 \mu\text{A}$		
220 mA to 2,2 A	40 Hz to 1 kHz	$70 \times 10^{-5} \times I + 35 \mu\text{A}$		
2,2 A to 11 A	40 Hz to 1 kHz	$65 \times 10^{-5} \times I + 200 \mu\text{A}$		

## Impedance (DC/LF)

### Measure

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 Ω to 2 Ω	DC	( $18 \times 10^{-6} \times R + 5,0 \mu\Omega$ ) or $20 \mu\Omega^1$	<ul style="list-style-type: none"> <li>• measure</li> <li>• 4-wire resistance measurement</li> <li>• negligible dissipated power</li> </ul>	P2-02-E.019.C
2 Ω to 20 Ω	DC	$10 \times 10^{-6} \times R + 15 \mu\Omega$		
20 Ω to 200 Ω	DC	$10 \times 10^{-6} \times R + 50 \mu\Omega$		
200 Ω to 2 kΩ	DC	$10 \times 10^{-6} \times R + 500 \mu\Omega$		
2 kΩ to 20 kΩ	DC	$10 \times 10^{-6} \times R + 5 \text{ m}\Omega$		
20 kΩ to 200 kΩ	DC	$10 \times 10^{-6} \times R + 50 \text{ m}\Omega$		
0,2 MΩ to 2 MΩ	DC	$11 \times 10^{-6} \times R + 1,2 \Omega$		
2 MΩ to 20 MΩ	DC	$25 \times 10^{-6} \times R + 120 \Omega$		
20 MΩ to 200 MΩ	DC	$13 \times 10^{-5} \times R + 12 \text{ k}\Omega$		
200 MΩ to 2 GΩ	DC	$16 \times 10^{-4} \times R + 1,2 \text{ M}\Omega$		

<sup>1</sup> Whichever is greater

### Generate

Generating range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
0 Ω	DC	$100 \mu\Omega$	<ul style="list-style-type: none"> <li>• generate</li> <li>• fixed points</li> <li>• 4-wire resistance</li> <li>• lowest possible power dissipation</li> <li>• * 2-wire resistance</li> </ul>	P2-02-E.039.C
1 Ω, 1,9 Ω	DC	$12 \times 10^{-5} \times R$		
10 Ω, 19 Ω	DC	$35 \times 10^{-6} \times R$		
100 Ω, 190 Ω	DC	$20 \times 10^{-6} \times R$		
1 kΩ, 1,9 kΩ, 10 kΩ, 19 kΩ, 100 kΩ, 190 kΩ	DC	$17 \times 10^{-6} \times R$		
1 MΩ, 1,9 MΩ	DC	$30 \times 10^{-6} \times R$		
10 MΩ, 19 MΩ	DC	$60 \times 10^{-6} \times R$		
100 MΩ*	DC	$15 \times 10^{-5} \times R$		

### Calibration of resistor / insulation meters

Measuring range or point	Resistance	expanded uncertainty (*)	Remark	Calibration procedure
50 V to 250 V	10 kΩ to 40 MΩ	$1,0 \times 10^{-4} \times R$		P2-02-E.017
	40 MΩ to 200 MΩ	$5,0 \times 10^{-4} \times R$		
250 V to 1000 V	100 kΩ to 200 MΩ	$1,0 \times 10^{-4} \times R$		
	200 MΩ to 1000 MΩ	$3,0 \times 10^{-4} \times R$		

### Capacity

Measuring range or point	Frequency	expanded uncertainty (*)	Remark	Calibration procedure
1 μF	From 20Hz to 1 kHz	0,50%	Capacitance generation on all DUTs with a "capacitance measurement" function with a sinusoidal measurement signal	P2-02-E.053
10 μF				

(\*) the smallest uncertainty of measurement the laboratory can provide to its customers, expressed as the expanded uncertainty having a coverage probability of approximately 95%.